

SS30

Professional FM Transceiver VHF/UHF Portable

TIME OUT TIMER

The time out timer is used to prevent any caller from using a channel for extended period of time.

BATTERY SAVE

The battery save function decreases the amount of power when the radio is not in transmit or receive for more than 10 seconds

CHANNEL NUMBER ANNUNCIATION

The voice annunciation on the SS30 allows you to hear what channel the radio is on.

SELECTABLE OUTPUT POWER

The SS30 allows you to select the power from high power to low power to save battery life.

$SS30_{\hbox{Professional VHF/UHF Transceiver}}$

| General | |
|----------------------------------|-------------------------------|
| Frequency Range | VHF 136-174 |
| | UHF 400-470MHz, 450-520MHz |
| Channel Capacity | 16 |
| Channel Spacing | 12.5/25.0KHz |
| Operation Voltage | 7.4V |
| Battery Capacity | 1500mAh(Li-ion) |
| Battery Life (5-5-90 Duty Cycle) | About 15 Hours |
| Frequency Stability | ±2.5ppm |
| Operating Temperature | -20~ +60°C |
| Antenna Impedance | 50Ω |
| Dimension*W*D) (Without Antenna) | 107*54*31mm |
| Weight (With Antenna & Battery) | 225g |
| Transmitter | |
| RF Power Output | UHF:5.0W/1W, VHF 5W/1W |
| Modulation Type | F3E |
| Spurious and Harmonics | -36dBm<1GHz; -30dBm>1GHz |
| FM Noise | 45/40dB |
| Audio Distortion | ≤5% |
| Modulation Limiting | ±2.5KHz@12.5KHz;±5.0KHz@25KHz |
| Audio Response | +1 to -3dB |
| Receiver | |
| Sensitivity | ≤0.3/0.2 uV |
| Adjacent Channel Selectivity | 60/70dB |
| Intermodulation | 65dB |
| Spurious Response Rejection | 70dB |
| S/N | 45/40dB |
| Audio power Output | 600mW |
| Audio Distortion | ≤5% |